Three phase electricity meters B23/B24 EQ meters in Steel version from ABB

The compact and versatile EQ meters B23 and B24 are three phase meters with outstanding performance. They can be used in most of the common applications for reliable and trustworthy metering of energy usage.

EQ meters B23/B24 in Steel version can be used in stand-alone applications or metering network installations with the option of inbuilt M-Bus or Modbus.



General features

B23 is a three phase direct connected meter up to 65 A and B24 is a three phase transformer connected for 5 A. The B23 and B24 are measuring active energy with accuracy class B (Cl. 1). The low rated or base currents of these products ensures high dynamic performance with superior accuracy even at low currents. Navigation of the meters is easily done via the push-buttons below the display. The exceptional low power consumption of the meters, less than 1.6 VA, makes them economical in the long run-an important feature specially for large meter populations.

Communication

Data from B23 and B24 can be collected via pulse output or serial communication. The meters are equipped with a transistor output for 5-40 VDC external supply. It can be used for pulses proportionally to the measured energy or various alarms. The meters are also available with built-in serial communication interfaces for Modbus RTU (RS-485) or M-Bus as options.

Instrumentation

The B23 and B24 meters support reading of instrument values. A large number of electrical properties can be read.

- Active power Total and per phase
- · Voltage Total and per phase
- Current Total and per phase
- Power factor
- Frequency

Approvals

The B23 and B24 meters are type approved according to IEC as well as type approved and verified according to MID. MID is the Measure Instruments Directive 2004/22/EC from European Commission. The type approval is according to standards that covers all relevant technical aspects of the meter. These include climate conditions, electromagnetic compatibility (EMC), electrical requirements, mechanical requirements and accuracy.

Ordering details

65 A direct connected, 4 DIN

Voltage V	Communication	Туре	Order code	Weight 1 pc					
Steel Active energy, pulse output, class B (Cl. 1)									
3 x 230/400 V AC	-	B23 111 - 100	2CMA100163R1000	0.31					
	RS-485	B23 112 - 100	2CMA100164R1000	0.32					
	M-Bus	B23 113 - 100	2CMA100165R1000	0.33					

6 A transformer connected, 4 DIN

Voltage V	Communication	Туре	Order code	Weight 1 pc
Steel Active energy, puls	e output, class B (0	Cl. 1)		
3 x 230/400 V AC	-	B24 111 - 100	2CMA100177R1000	0.25
	RS-485	B24 112 - 100	2CMA100178R1000	0.25
	M-Rus	B24 113 - 100	2CMA100179R1000	0.27





B series Technical data

	B23	B24						
Voltage/current inputs								
Nominal voltage	3x230/400 V AC							
Voltage range	3x220-240 VAC (-20% - +15%)							
Power dissipation voltage circuits	1.6 VA (0,7 W) total							
Power dissipation current circuits	0.007 VA (0.007 W) per phase at 230 V AC and I _b							
Base current I _b	5 A	-						
Rated current In	-	1 A						
Reference current I _{ref}	5 A	-						
Transitional current I _{tr}	0.5 A 0.05 A							
Maximum current I _{max}	65 A 6 A							
Minimum current I _{min}	0.25 A 0.02 A							
Starting current I _{st}								
Terminal wire area								
Recommended tightening torque	1 - 25 mm² 0.5 - 10 mm² 3 Nm 1.5 Nm							
	3 1011	1.5 NIT						
Communication	0 E 1 mm ²							
Terminal wire area	0.5 - 1 mm ²							
Recommended tightening torque	0.25 Nm							
Transformer ratios	-							
Configurable current ratio (CT)	-	1/9 - 9999/1						
Pulse indicator (LED)								
Pulse frequency	1000 imp/kWh	5000 imp/kWh						
Pulse length	40 ms	40 ms						
General data		÷						
Frequency	50 or 60 Hz ± 5%							
Accuracy Class	B (Cl. 1)							
Active energy	1%	······						
Display of energy Environmental	7 digit LCD							
	4000							
Operating temperature	-40°C - +70°C							
Storage temperature	-40°C - +85°C							
Humidity	75% yearly average, 95% on 30 days/year							
Resistance to fire and heat	Terminal 960 °C, cover 650°C							
Resistance to water and dust		protective enclosure and IP51 in protective enclosure,						
Mechanical environment	according to IEC 60529.	he Measuring Instrument Directive (MID). (2004/22/EC)						
		ne Measuring Instrument Directive (MID). (2004/22/EC) ne Measuring Instrument Directive (MID), (2004/22/EC).						
Electromagnetic environment	UIASS EZ III AUCUIUAIICE WILLI LI	ie weasuning instrument birective (WID), (2004/22/EC).						
Outputs	0 100 mA							
Current	2 - 100 mA							
Voltage	5 - 40 VDC.	- 0.540-						
Pulse output frequency	Programmable: 1 - 999999 im	ip/kWh						
Pulse length	Programmable: 10 - 990 ms							
Terminal wire area	0.5 - 1 mm ²							
Recommended tightening torque	0.25 Nm							
EMC compatibility								
Impulse voltage test	6 kV 1.2/50µs (IEC 60060-1)							
Surge voltage test	4 kV 1.2/50µs (IEC 61000-4-5)						
Fast transient burst test	4kV (IEC 61000-4-4)							
Immunity to electromagnetic HF-fields	80 MHz - 2 GHz (IEC 61000-4	I-6)						
Immunity to conducted disturbance	150kHz - 80MHz (IEC 61000-							
-	2kHz - 150kHz							
Radio frequency emission	EN 55022, class B (CISPR22)							
Electrostatic discharge	15 kV (IEC 61000-4-2)							
Standards	· · · · · · · · · · · · · · · · · · ·	lass 1, GB/T 17215.211-2006, GB/T 17215.312-2008						
		470-1, EN 50470-3 category B						
Mechanical								
Material	Polycarbonate in transparent fi	ront glass. Glass reinforced polycarbonate in bottom						
	case and upper case. Polycarl							
Dimensions								
Width	70 mm							
Height	97 mm							
	65 mm							
Depth	65 mm							

Wiring diagram B23

3 wire connection, 2 elements



4 wire connection, 3 elements



Wiring diagram B24

3 wire connection, 2 elements

V	123	5	78	9 11	S1 S2
L1 L2 L3	P1		P1		

4 wire connection, 3 elements

Y	1	2	3	4	5	6	7	8	9	11	1 5	\$1 S2
L1	P1			P	1		P	1			F	$P1 \longrightarrow P2$
L2 L3 N			_							-		

ABB AB

Meters Box 1005 SE-611 29 NYKÖPING, Sweden Telephone +46 155 29 50 00 Telefax +46 155 28 81 10

www.abb.com

 $\ensuremath{\mathbb{O}}$ Copyright 2014 ABB. All rights reserved. Specification subject to change without notice.



This QR-code is linked to our web site www.abb.com/lowvoltage. You will have to download a QR-code reader app to your phone in order to use it.

CE

